



V1300C2, DV1300C2, V1311C2-A

- crimping of Cu terminals 10 - 400 mm²



V1300C2

Crimp head for crimping of Cu terminals 10-400 mm² and C-sleeves up to 120 mm². Used with footpump P4000 or battery/mains powered pump PS710.

Particulars:

- lockable and rotatable handle (360°)
- equipped with oil spray safety protection cap
- working pressure 63 MPa (630 bar)
- crimp force 130 kN
- flexible and easy to operate
- weight 4,9 kg excl accessories
- length 297 mm, incl fork and quick coupling

DV1300C2

C-fork type crimp head, open to one side, used with footpump P4000 or battery/mains powered pump PS710.



Particulars:

- lockable and rotatable handle (360°)
- crimp head with the patented DUAL CRIMP technique which starts with an optimized hexagonal crimp and then makes a small indent in the same crimp cycle to further improve gas tightness as well as electrical and mechanical properties.
- DUAL dies are available for 10-300 mm²
- crimp terminals type KRF and through connectors type KSF
- conventional dies as for V1300C2 can be used (without DUAL-function)
- DV1300C2 can also be used with regular crimp dies for the 1300C-system

V1311C2-A

Hydraulic handtool, uses the same die system as V1300C2.

Particulars:

- automatic two-step fast feed system
- full closure system which guarantees a complete crimp
- the fork is rotatable 180°
- crimp force 130 kN
- ergonomically shaped handles
- easy to carry and operate
- covers the common needs of Cu-crimping for electricity utilities
- weight 5,9 kg, excl accessories
- length 626 mm
- crimp range 10-400 mm²
- incl. carry box



V1300C2, DV1300C2, V1311C2-A

Accessories for crimping Cu terminals

Dies for Cu-terminals and connectors

Supplied as a pair. For hexagonal crimping of Cu terminals and connectors.

If not indicated otherwise, always use outer die holder **V13C2**.

When using Bxx dies, also use die holder **V1330**.




Die pair 13CB27, to be used with die holder V13C2.


Die holder V1330 + B-dies, to be used with die holder V13C2.



Die pair 13C2B38, to be used without die holder V13C2.




One and two crimps.



Three crimps.



Die holder V1330 + BC6-dies.



One or two crimps.

KRF/KSF				
mm ²	Dies	No. of crimps	DUAL dies	No. of crimps
10	B8	1	13DCB8	1
16	B9	1	13DCB9	1
25	B11	1	13DCB11	1
35	B13	1	13DCB13	1
50	B14,5	1	13DCB14,5	1
70	B17	1	13DCB17	1
95	B20	1	13DCB20	1
120	B22	1	13DCB22	2
150	B25	1	13DCB25	2
185	13CB27	2	13DCB27	2
240	13CB30	2	13DCB30	2
300	13CB32	2	13DCB32	2
400	13C2B38*	3	-	-

*Used without die holder V13C2

mm ²	KRD/KSD		KRT/KST		DIN46235	
	Dies	No. of crimps	Dies	No. of crimps	Dies	No. of crimps
10	B8	1	B7	1	B6DIN	1
16	B8	1	B8,5	1	B8DIN	1
25	B9	1	B10	1	B10DIN	1
35	B11	1	B12	1	B12DIN	1
50	B12	1	B14	1	B14DIN	1
70	B14	1	B16	1	B16DIN	1
95	B16	1	B18	1	B18DIN	1
120	B19	1	B19	1	B20DIN	1
150	B22	1	B22	1	B22DIN	1
185	13CB25	2	13CB24	2	-	-
240	13CB27	2	13CB26	2	-	-
300	13CB30	2	13CB30	2	-	-
400	13CB32	2	13CB32	2	-	-

Dies for C-sleeves

For oval crimping of Cu branch connectors (C-sleeves).

If not indicated otherwise, always use outer die holder **V13C2**.

When using Bxx dies, also use die holder **V1330**.

Main conductor mm ²	Branch mm ²	Dies	No. of crimps
10-6	10-6	BC4**	1
16-10	16-6	BC5	1
25-16	25-16	BC6	1
50-16	50-16	BC8-9	1
70-50	70-25	BC11	1
95-70	95-25	13CBC13*	2
120-95	120-25	13CBC15*	2

*Used without die holder V1330.

**Die nest must be marked C4A to connect 6 mm² main to 6 mm² branch.